INSTRUCTIONS FOR MAINTENANCE

BOBRICK SANITARY NAPKIN/TAMPON VENDORS - MODELS B-37063, B-370634, and B-370639

MAINTENANCE

To load Dispensers:

Insert 20 napkin packages, measuring between 2-7/8" x 3/4" x 4-1/8" to 3-1/8" x 1-1/8" x 4-3/8" (73 x 19 x 105mm to 80 x 29 x 111mm) in the napkin magazine (see Advisory Bulletin TB-25). Then insert 30 tampons, measuring between 4-5/8" long x 9/16" diameter minimum to 5-1/8" long x 3/4" diameter maximum (118 x 14mm to 130 x 19mm) in the tampon magazine.

To empty Coin Box: (25¢ and 50¢ only)

Unlock coin box lock with key provided and pull forward to remove. Empty coin box then reinsert coin box ensuring rectangular feet are fully inserted into coin box bracket mounting slots (see Fig. A). Lock coin box into place.

To dispense Napkin or Tampon:

Insert coin(s) in coin slot (25¢ and 50¢ only), push button as far as it will go and release. When one napkin or tampon is left, the napkin or tampon red empty indicator blocks the coin slot to prevent another coin from being inserted and indicates time to refill.

If Vendor fails to work properly, ensure that:

- 1. Machine is loaded with correct size napkins and tampons.
- 2. Damaged napkins or tampons are not jamming mechanism.
- 3. Coin box is seated properly on coin box bracket. (25¢ and 50¢ only)
- 4. Coin box is not full. (25¢ and 50¢ only)

To replace individual Magazine Assembly:

Order applicable Free. 25¢ or 50¢ Napkin and/or Tampon Magazine Assembly Kit. Remove napkins and/or tampons from vendor. Remove existing magazine by unscrewing two (2) hex nuts from each magazine assembly as indicated in figure B; install new magazine assembly using same hex nuts.

To replace Bezel Assembly:

Remove existing bezels from the door by removing three (3) plastite screws from each bezel assembly on the door. Install new bezels ensuring that the locating pins are properly engaged and reinstall existing screws. Refer to replacement parts for correct Bezel assembly.

To replace Product Tray Kit:

Order Part No. 3706-60. Remove four (4) plastite screws from bottom of cabinet and remove tray. Install new tray using same screws. If unit is recessed, unit must be removed from wall to access screws for product tray replacement.

To replace Door Locks:

Order 2 each Part No. 383257 or 3706-175. Remove lock nut from inside of door. Install new locks, securing them with new


To replace Door:

3706-197

Order Part No. 3706-156 for Free operation, 37063-157 for 25¢ or 37063-158 for 50¢. Unlock and open door. Use nail or similar object to push hinge pin out of hinge knuckle and use pliers to pull hinge pin out. Remove door. Using same hinge pin, align hinge knuckles of new door with the cabinet and insert pin from top. Ensure hinge pin is aligned flush at top or bottom of hinge barrel and filed smooth.


	REPLACEMENT PARTS (refer to Fig. B)	
(A)	Product Tray Kit	3706-60
	Coin Box Kit	3706-344
(C)	Door Assembly Kit, Free	
_	(includes Bezel Assemblies)	37063-156
(D)	Door Assembly Kit, 25¢	
	(includes Bezel Assemblies)	37063-157
E	Door Assembly Kit, 50¢	
	(includes Bezel Assemblies)	37063-158
E	Tampon Bezel Assemby Kit Free	3706-288
G	Napkin Bezel Assemby Kit Free	3706-289
	Tampon Bezel Assemby Kit 25¢	3706-191
①	Napkin Bezel Assemby Kit 25¢	3706-192
(j)	Tampon Bezel Assemby Kit 50¢	3706-193
\mathbb{K}	Napkin Bezel Assemby Kit 50¢	3706-194
(L)	Tampon Magazine Assemby Kit Free	3706-294
02000CC	Napkin Magazine Assemby Kit Free	3706-295
\mathbb{N}	Tampon Magazine Assemby Kit 25¢	3706-205
0	Napkin Magazine Assemby Kit 25¢	3706-206
(P)	Tampon Magazine Assemby Kit 50¢	3706-215
Q	Napkin Magazine Assemby Kit 50¢	3706-216
\mathbb{R}	Door Lock & Key (keyed to Cat 74)	383257
S	Door Lock & Key	
_	(keyed to Cat 118 for added security)	3706-175
1	2" Skirt for Semi-Recessing	370634-17

Fig. A Coin Box Coin Box Feet (2)



IMPORTANT NOTE:

Ensure coin box round feet are engaged in coin box bracket.





6" Skirt for Surface-Mounting

In the U.S.A.: BOBRICK WASHROOM EQUIPMENT, INC.

370639-18

200 Commerce Drive, Clifton Park, New York 12065-1350; Telephone: 518-877-7444 • FAX: 518-877-5029 6901 Tujunga Avenue, North Hollywood, California 91605-6213; Telephone: 818-982-9600 • FAX: 818-503-9287 or email customerservice@bobrick.com

In Canada: BOBRICK WASHROOM EQUIPMENT COMPANY

45 Rolark Drive, Scarborough, Ontario M1R 3B1 Eastern Canada: 877.423.6555 • Fax: 423.765.8555 • Western Canada: 877.423.6444 • Fax: 423.503.8444


INSTRUCTIONS FOR CONVERSION

BOBRICK ADA COMPLIANT SANITARY NAPKIN/TAMPON VENDOR MODELS B-2706, B-3706, B-37063, B-370634, B-370639, B-4706, B-47064

To Convert Coin Denomination:

From 25¢ or 50¢ to Free

- 1. Remove Ratchet Pawl Fig 1 (A1) and Extension Spring, Fig 1 (A2)
- 2. Remove Machine Screw Fig 1 (B1) and Damper Gear Rack Fig 1 (B2)
- 3. Install Free Vend Lever (included in kit) where Damper Gear Rack in Fig. 1 (B2) was removed. Hemmed tab of Damper Gear Rack must face the magazine (see figure 1 B1) and reinstall screw.





In the U.S.A.: BOBRICK WASHROOM EQUIPMENT, INC.

200 Commerce Drive, Clifton Park, New York 12065-1350; Telephone: 518-877-7444 • FAX: 518-877-5029 6901 Tujunga Avenue, North Hollywood, California 91605-6213; Telephone: 818-982-9600 • FAX: 818-503-9287 or email customerservice@bobrick.com

In Canada: BOBRICK WASHROOM EQUIPMENT COMPANY


INSTRUCTIONS FOR CONVERSION

BOBRICK ADA COMPLIANT SANITARY NAPKIN/TAMPON VENDOR MODELS B-2706, B-3706, B-37063, B-370634, B-370639, B-4706, B-47064

To Convert Coin Denomination:

From Coin to Token, 50¢ to 25¢

- 1. Remove two (2) machine screws (T15 Torx Drive) from each of the 25¢ Coin Return Lever Assemblies at the locations indicated in figure A.
- 2a. For conversion from 25¢ to token, order part number 3706-166: Install Token Coin Lever Assembly (included with kit) so that the 25¢ embossment is on top (see figure A2) and reinstall screws.
- 2b. For conversion from 50¢ to 25¢, order part number 3706-161: Install 25¢ Coin Return Lever Assemblies (included with kit) so that the 25¢ embossment is on top (see figure A2) and reinstall screws
- Adhere coin label (included with kit) onto existing Bezels to match the coin denomination of the magazine. Adhere Napkin graphics label on left Bezel and Tampon graphics label on right Bezel.





200 Commerce Drive, Clifton Park, New York 12065-1350; Telephone: 518-877-7444 • FAX: 518-877-5029 6901 Tujunga Avenue, North Hollywood, California 91605-6213; Telephone: 818-982-9600 • FAX: 818-503-9287 or email customerservice@bobrick.com

INSTALLATION INSTRUCTIONS FOR BEZEL ASSEMBLY

BOBRICK ADA COMPLIANT SANITARY NAPKIN/TAMPON VENDOR MODELS B-2706, B-3706, B-37063, B-370634, B-370639, B-4706, B-47064, B-47069

To Replace Bezel Assembly:

Remove existing Bezels from the door by removing three (3) Plastite screws (T15 Torx Drive) from each Bezel assembly at the back of the door (see figures A & B). Install new Bezels ensuring that the locating pins are properly engaged in the door pilot holes and reinstall existing screws (see figures A & B).

Back View of Door Plastite Screws (T15 Torx) Fig. A Locating Pins Plastite Screws (T15 Torx) Napkin Bezel Assembly For ClassicSeries' Model Numbers B-2706. B-3706 and TrimLineSeries™ Model Numbers B-37063, B-370634, B-370639 Tampon Bezel Assembly Kit 25¢ Napkin Bezel Assembly Kit 25¢ Tampon Bezel Tampon Bezel Assembly Kit 50¢ Napkin Bezel Assembly Kit 50¢ Assembly Tampon Bezel Assembly Kit Free (Not shown) Napkin Bezel Assembly Kit Free (Not shown) Tampon Bezel Assembly Kit Token Fig. B Napkin Bezel Assembly Kit Token For ConturaSeries' Model Numbers B-4706, B-47064, B-47069 Tampon Bezel Assembly Kit 25¢ Napkin Bezel Assembly Kit 25¢



Tampon Bezel Assembly Kit 50¢

Napkin Bezel Assembly Kit 50¢

Tampon Bezel Assembly Kit Free (Not shown)

Napkin Bezel Assembly Kit Free (Not shown)

3706-191

3706-192

3706-193

3706-194

3706-195

3706-196

3706-197

3706-198

4706-191

4706-192

4706-193

4706-194

4706-195

4706-196

In the U.S.A.: BOBRICK WASHROOM EQUIPMENT, INC.

200 Commerce Drive, Clifton Park, New York 12065-1350; Telephone: 518-877-7444 • FAX: 518-877-5029 6901 Tujunga Avenue, North Hollywood, California 91605-6213; Telephone: 818-982-9600 • FAX: 818-503-9287 or email customerservice@bobrick.com

Front

INSTRUCTIONS FOR MAGAZINE REPLACEMENT

BOBRICK ADA COMPLIANT SANITARY NAPKIN/TAMPON VENDOR MODELS B-2706, B-3706, B-37063, B-370634, B-370639, B-4706, B-47064

TOOLS REQUIRED: Ratchet with 3/8" Socket

To replace individual Magazine Assembly:

Note: Remove napkin boxes and/or tampon tubes from vendor before replacing Magazine Assemblies.

- Unlock and remove Coin Box from unit.
- Remove two (2) Hex nuts (#10-32) from each Napkin and Tampon Magazine Assemblies using a ratchet with 3/8" socket.
- Pull Napkin Magazine forward and out of cabinet.
- 4. Pull Tampon Magazine forward and out of cabinet.
- Install new Napkin and Tampon Magazine Assemblies into cabinet in the reverse order as they were removed and reinstall existing Hex nuts.
- 6. Replace Coin Box into position below magazines and lock in place.

REPLACEMENT PARTS

For ClassicSeries' Model Numbers B-2706, B-3706 and TrimLineSeries™ Model Numbers B-37063. B-370634. B-370639

_		
F	roc	١
		۶

3706-256 Door Assembly Kit, Free (includes Bezel Assemblies)

3706-195 Tampon Bezel Assembly Kit Free 3706-196 Napkin Bezel Assembly Kit Free

3706-294 Tampon Magazine Assembly Kit Free

3706-295 Napkin Magazine Assembly Kit Free

Token

3706-166 Token Conversion Kit

3706-197 Tampon Bezel Assembly Kit Token

3706-198 Napkin Bezel Assembly Kit Token

3706-296 Tampon Magazine Assembly Kit Token

3706-297 Napkin Magazine Assembly Kit Token

3706-405 Tokens (qty. 100)

25¢

3706-157 Door Assembly Kit, 25¢ (includes Bezel Assemblies)

3706-191 Tampon Bezel Assembly Kit 25¢

3706-192 Napkin Bezel Assembly Kit 25¢

3706-205 Tampon Magazine Assembly Kit 25¢

3706-206 Napkin Magazine Assembly Kit 25¢

50¢

3706-215 Tampon Magazine Kit

3706-216 Napkin Magazine Kit

3706-193 Tampon Bezel Assembly Kit 50¢

3706-194 Napkin Bezel Assembly Kit 50¢

Universal

3706-60 Product Tray Kit


3706-344 Coin Box Kit

383257 Door Lock & Key (keyed to Cat 74)

3706-175 Door Lock & Key (keyed to Cat 118 for added security)

370634-17 2" Skirt FOR Semi-Recessing

370639-18 6" Skirt for Surface-Mounting





In the U.S.A.: BOBRICK WASHROOM EQUIPMENT, INC.

200 Commerce Drive, Clifton Park, New York 12065-1350; Telephone: 518-877-7444 • FAX: 518-877-5029 6901 Tujunga Avenue, North Hollywood, California 91605-6213; Telephone: 818-982-9600 • FAX: 818-503-9287 or email customerservice@bobrick.com